



STEP MOTION CONTROLLER

6-Channel Closed-loop Control; Adapt To All Linear Tables, Rotary Tables And Tilter Tables; Programming Control

MULTI-FIELD LOW TEMPERATURE
TECHNOLOGY (BEIJING) CO., LTD.

www.multi-field.com

Room 505, 5th Floor, Building 2, No.
11, Xingke East Street, Yanqi
Economic Development Zone, Huairou
District, Beijing, P.R.China

Step Motion Controller, Specification

LT-MotionCenter	
Compatible Positioner	Linear Positioner, Rotator, Goniometer
Control Mode	All Channels Closed-Loop Control
Size	19"/3U
Work Voltage & Power Consumption	220 VAC & 60 W
Remote	Serial Port
Output Channels	6 Channels
Max Output Voltage	-200 V ~ +200 V
Drive Frequency Range	1 ~ 10 kHz
Power for 1 Channel	Max. 40 W
Slew Rate	2 kV/us
GND in Drive Output	6 Channels Independent GND
Encoder	Resistive Encoder
Sensor Output Voltage	DC 2.5 V
Resolution of Read Voltage	50 μ V (18-bit)
Input Channels	6 Channels
Input Resistance	10 kOhm
GND in Sensor Readout	6 Channels Independent GND
Electrical Connector	D-sub 15 for Each Channel
Connector Schematic	/